


EX-328



Rating: Not Rated Yet

[Ask a question about this product](#)

Description	Input Connectors	: 1/4" TRS, female XLR (pin 2 hot)
	Input Type	: Electronically balanced/unbalanced, RF filtered
	Input Impedance	: Balanced 40 kOhm, unbalanced 20 kOhm
	Max Input	: >+21dBu balanced or unbalanced
	CMRR	: >40dB, typically >55dB at 1kHz
	Output Connectors	: 1/4" TRS, male XLR (pin 2 hot)
	Output Type	: Impedance-balanced/unbalanced, RF filtered
	Output Impedance	: Balanced 100 ohm, unbalanced 50 ohm
	Max Output	: >+21dBu balanced/unbalanced into 2 kOhm or greater; >+18dBm balanced/unbalanced (into 600 ohm)
	Bandwidth	: 20Hz to 20kHz, +0.5/-1dB
	Frequency Response	: 50kHz, +0.5/-3dB
	Dynamic Range	: Typically >112dB
	Signal to Noise Ratio	: Typically >95dB
	THD+Noise	: <0.003%
	Interchannel Crosstalk	: <-90db, 20Hz to 20kHz
	Bypass Switch	: Bypasses the graphic equalizer section in the signal path

Low cut Switch	: Activates the 50Hz 12dB/octave Bessel high-pass filter
Range Switch	: Selects either +/- 6dB or +/- 12dB slider boost/cut range
Operating Voltage	: 100VAC-240VAC 50/60Hz
Power Consumption	: 15W
Power Connector	: IEC receptacle
Unit Weight	: 4.8 lbs.(2.2 kg)
Shipping Weight	: 6.2 lbs.(2.8kg)
Dimensions	: 1.75\'' (4.4cm) H x 6\''(15.24cm) D x 19\'' (48.26cm) W