

amplifier LX-9100



Rating: Not Rated Yet

[Ask a question about this product](#)

| | | |
|-------------|--------------------------------|----------------|
| Description | Audio Output (4 O) | : 450W+450W |
| | Sensitivity Mic Input | : 10mV |
| | External device Sensitivity | : 200mV |
| | Signal: (IHF A Filter) | : 80dB |
| | T.H.D. (1KHz, AUX 150mV Input) | : 0.1% |
| | Frequency band | : 25Hz~20kHz |
| | Mic. Tone Adjustment | : 80Hz ± 15dB |
| | | : 3.5Hz ± 8dB |
| | Echo Tone Adjustment | : 12KHz ± 15dB |
| | | : 80Hz ± 15dB |
| | Power Source | : AC220V/50Hz |
| | Electricity Consumption | : 900W |
| | Weight | : 9KG |

Dimension (mm)

: 440(W)x180(H)x380(D)